



## Wireless Solutions for Fire & Security

### FireCell Sounder

- Fully addressable
- Wireless activation
- Third party approved (EN54)
- 2-way radio communication
- 5 year battery life at normal conditions
- 32 selectable tones
- Beacon option
- Acoustic self test
- Universal transmitter module
- Transmitter tamper
- Range in excess of 150 metres



### Overview

The model FCX-300-002 Radio Sounder is a battery operated sounder remotely activated and monitored by the controller. Each unit has a unique address configured during manufacture and is individually addressable by the system controller. Each unit is controlled individually or by zone, dependant on the system design.

The radio sounder is housed in an industry standard, impact resistant ABS moulding. The sounder has 2-way radio communication with the fire system controller using 868MHz wavebands to receive command instructions for auto reporting.

Designed and manufactured using the latest techniques and surface-mount technology ensures component count is kept to a minimum, thereby maximising reliability.

The sounder is powered by a low-voltage dual supply alkaline battery pack. The battery pack condition is continually monitored. The battery board has been tested to provide a 5 year battery life at normal conditions. The system indicates remaining battery capacity and a low battery condition is indicated to the controller as a fault, leaving approximately 30 days for the battery pack to be changed.



## Specification

Dimensions:	120 x 125 mm with transmitter/address module Weight 0.65Kg
Operating Temperature:	-10 to 70 °C
Humidity:	Up to 95% non-condensing
Supply:	3 x AA & 3 x C cell Duracell Alkaline batteries
IP Rating	IP54
Sounder Output	99 dBA @1m (as dispatched)
Operating Frequencies:	868 MHz
Output Transmitter Power:	Variable 0-14dBm
Standards:	Third party certified to; EN54 part 3 EN54 part 25 ENTSI 300:220

## Ordering Information

radio sounder includes base and batteries:

Part Number **FC-300-002**

radio sounder radio base only:

Part Number **FC-171-002**

red sounder head:

Part Number **FC-172-002**

red sounder beacon

Part Number **FC-173-002**



EMS Group Head Office  
Technology House  
Sea Street  
Herne Bay  
Kent CT6 8JZ  
England  
Tel: +44 (0) 1227 369570  
Fax: +44 (0) 1227 369679  
Email: [enquiries@msgroup.co.uk](mailto:enquiries@msgroup.co.uk)

[www.msgroup.co.uk](http://www.msgroup.co.uk)

An ISO9001:2008 approved company



Dealer Information:

Part No: Firecell 6, v1.5

The information contained within this literature is correct at time of publishing. The EMS Group reserves the right to change any information regarding products as part of its continual development enhancing new technology and reliability. The EMS Group advises that any product literature issue numbers are checked with its head office prior to any formal specifications being written.